



## Signamax™ Connectivity Systems

**Fast Ethernet media converters  
10Base-T/100Base-TX to 100Base-FX  
series**

**Model:065-1176**

### **User's Manual**



## FCC Warning

This device has been tested and found to comply with limits for a Class A digital device, pursuant to Part 2 and Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses and radiates radio frequency energy and, if not installed and used in accordance with the user's manual, may cause interference in which case user will be required to correct the interference at his own expense.

### NOTICE:

1. The changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
2. Shielded interface cables and AC power cord, if any, must be used in order to comply with the emission limits.

### CISPR A COMPLIANCE:

This device complies with EMC directive of the European Community and meets or exceeds the following technical standard.

**EN 55022** - Limits and Methods of Measurement of Radio Interference Characteristics of Information Technology Equipment. This device complies with CISPR Class A.

### WARNING:

This is a Class A product. In a domestic environment, this product may cause radio interference in which case the user may be required to take adequate measures.

**Table of contents**

Chapter

1.....

5

Introduction.....

.....5

Product

Features.....

.....6

Technical

Specifications.....

.....7

Chapter

2.....

8

Package

contents.....

.....8

Model

information.....

.....9

Chapter

3.....

11

Installation.....

.....11

The LED  
indicators.....  
. . . . 12

Chapter  
4.....  
12  
Application.....  
. . . . 12

## **Chapter 1.**

### **Introduction**

The Fast Ethernet media converters series are designed to bridge a 100Base-TX signal to a 100Base-FX signal. It's used to extend the connection distance between two Fast Ethernet Twisted-pair devices via fiber cable transparently with no performance degradation.

The converter series is base on switching hub design. It's supported Auto-negotiation & flow control function on Twisted-pair port. And provided different types of fiber connectors such as SC, ST, Bi-direction WDM, MT-RJ and LC for multi-mode or single-mode cables.

## Product Features

- Complies with IEEE802.3u 10Base-T/100Base-TX, 100Base-FX Standards.
- TP port support Auto-MDIX & Auto-negotiation.
- TP port up to 100 meters for shielded/unshielded twisted pair cable.
- Supports Full-duplex & Half-duplex operation on TP base on Auto-negotiation.
- Switch base design support flow control capability.
- Supports Full-duplex & Half-duplex operation on fiber by slide switch.
- 100Base-FX interface for up to 5km. (Use 50/125  $\mu\text{m}$  or 62.5/125  $\mu\text{m}$  MMF optic cable)
- 100Base-FX interface for up to 60 km. (Single-mode 9/125  $\mu\text{m}$  SMF optic cable)
- LED indicator supports.
- Multiple fiber connector supports. (SC, ST, Bi-direction WDM, MT-RJ, LC...etc)
- Supports fault propagation.
- Can be installed on media converter chassis.

## Technical Specifications

- Standards : IEEE 802.3u 10Base-T/100Base-TX and 100Base-FX
- Media support : 10BASE-T EIA/TIA 568 Cat3, 4, 5, 5e or 6 UTP/STP  
: 100Base-TX EIA/TIA 568 Cat5, 5e or 6 UTP/STP  
: 100Base-FX Multi-mode 50/125 µm & 62.5/125 µm MMF  
: 100Base-FX Single-mode 9/125 µm SMF
- Distances support : Twisted pair STP à 100meters  
: Multi-mode fiber: 415 meters for half-duplex.  
: Multi-mode fiber: 5km for full duplex.  
: Single-mode fiber: 415 meters for half-duplex.  
: Single-mode fiber: 60km for full duplex.
- Wavelength : 1310nm on Single/Multi-mode, 1310nm/1550nm  
Bi-direction WDM
- Data Transfer Rate : 100Mbps/10Mbps
- LED indicators : System - power  
: Twisted pair port – Link/Activity, Speed and FDX/Col  
: Fiber port – Link/Activity & FDX LEDs
- Temperature : 0° to 45° (Operating)  
: -20° to 90° (Storage)
- Humidity : 10% to 90% (Non-condensing)
- Power consumption : 3.4 Watts (max)
- Power Requirement : 5V DC 1A
- Certifications : FCC Class A, CE Mark
- Dimensions : 102 mm × 74 mm × 22 mm (L × W × H)
- Weight : 230g (No power adapter)

## Chapter 2.

### Package contents

Before you start to install the Switch, please verify your package that contains the following items:

- One media converter
- One Power Adapter
- One User's Manual



Media Converter



Power Adapter

CD with User's Manual





## Model information

### 100Base-FX Multi-Mode 1310nm wavelength

Model	Description
Multimode SC Connector	<ul style="list-style-type: none"> <li>■ 100Base-FX fiber port (<b>SC type MMF</b>)</li> <li>■ Up to 415 meters (1360 ft.) for MMF 50/125um or 62.5/125um optic cables on half-duplex operation.</li> <li>■ Up to 2, <b>5km</b> (1.24, <b>3.1</b> mi.) for MMF 50/125um or 62.5/125um optic cables on full-duplex operation.</li> </ul>
Multimode ST Connector	<ul style="list-style-type: none"> <li>■ 100Base-FX fiber port (<b>ST type MMF</b>)</li> <li>■ Up to 415 meters (1360 ft.) for MMF 50/125um or 62.5/125um optic cables on half-duplex operation.</li> <li>■ Up to 2, <b>5km</b> (1.24, <b>3.1</b> mi.) for MMF 50/125um or 62.5/125um optic cables on full-duplex operation.</li> </ul>
Multimode MT-RJ Connector	<ul style="list-style-type: none"> <li>■ 100Base-FX fiber port (<b>MT-RJ type MMF</b>)</li> <li>■ Up to 415 meters (1360 ft.) for MMF 50/125um or 62.5/125um optic cables on half-duplex operation.</li> <li>■ Up to 2km (1.24 mi.) for MMF 50/125um or 62.5/125um optic cables on full-duplex operation.</li> </ul>
Multimode LC type Connector	<ul style="list-style-type: none"> <li>■ 100Base-FX fiber port (<b>LC type MMF</b>)</li> <li>■ Up to 415 meters (1360 ft.) for MMF 50/125um or 62.5/125um optic cables on half-duplex operation.</li> <li>■ Up to <b>5km</b> (<b>3.1</b> mi.) for MMF 50/125um or 62.5/125um optic cables on full-duplex operation.</li> </ul>

**100Base-FX Single-Mode 1310nm/1550nm wavelength**

Model	Description
Single mode SC connector	<ul style="list-style-type: none"> <li>■ 100Base-FX fiber port (<b>SC type SMF</b>).</li> <li>■ Up to <b>10, 20, 40 or 60</b>km for SMF 9/125um optic cables on full-duplex operation.</li> </ul>
Single mode LC connector	<ul style="list-style-type: none"> <li>■ 100Base-FX fiber port (<b>LC type SMF</b>).</li> <li>■ Up to <b>20, 40 or 60</b>km for SMF 9/125um optic cables on full-duplex operation.</li> </ul>
Bi-direction WDM connector - BA	<ul style="list-style-type: none"> <li>■ 100Base-FX Bi-direction fiber port</li> <li>■ TX.1310nm</li> <li>■ RX.1550nm</li> </ul>
Bi-direction WDM Connector - BB	<ul style="list-style-type: none"> <li>■ 100Base-FX Bi-direction fiber port</li> <li>■ TX.1550nm</li> <li>■ RX.1310nm</li> </ul>

## Chapter 3.

### Installation

#### I. DC input & external power adapter

The external power supply adapter specification:

- AC input range from 90VAC to 260VAC.
- AC frequency range from 47Hz to 63Hz, TUV, CE, UL Safety.
- Power adapter DC output is +5VDC 1.5A
- The device DC input +5VDC 1A.

#### II. The TP port

The device TP port support Auto-MDIX, Auto-negotiation and Flow control functions. The cable length up to 100 meters for shielded/unshielded twisted pair cable. Allow users connect the converter to 10BASE-T and 100BASE-TX devices.

#### III. The Fiber port

The converter provided different types of fiber connectors such as SC, ST, MT-RJ and LC for multi-mode or single-mode fiber cables.

#### Full-Duplex or Half-Duplex operation on fiber port

The converter provided slide switch at right side of converter. The purpose of the slide switch is for fiber full-duplex or half-duplex operation. The factory default is full duplex as below chart.



## The LED indicators

LED	Color	Status	Description
Power	Yellow	On	Power on
FDX	Green	On	Full-duplex
		Off	Half-duplex
		Flashing	Partial collision occurs
10/100M	Green	On	Port is on the 100M status
		Off	Port is on the 10M status
LINK/ACT.	Yellow	On	10/100Mbps port for connection
		Flashing	10/100Mbps for data activating

## Chapter 4.

### Application

Single-Mode Fiber application

